

# T940


MODEL



**EUROTHERM**

CONTROLS  
DATA MANAGEMENT  
PROCESS AUTOMATION



## Process Supervisor Product Data



- Powerful controller with large application capacity
- Redundant processor option
- Open I/O network

## PROCESS SUPERVISOR

- Powerful Strategy Engine supporting continuous and sequential control
- Redundant processor option with automatic and seamless changeover
- Live replacement of processor and automatic initialisation
- Support for Ethernet, ARCnet and serial control network architecture
- Peer to peer control network for node and supervisory communications
- Open I/O network with simultaneous support for Profibus DP, Modbus RTU
- Redundant I/O communications support
- Reduced wiring cost with distributed I/O
- Flexible architecture



The Process Supervisor is a powerful and configurable strategy engine capable of performing both continuous and sequential control. It has evolved from the successful T103/T102/T100 Unit Controllers and is designed for large applications.

The optional redundancy of processor modules provides high availability solutions for process control and the


live replacement of processor modules prevents any interruption of the process

The Process Supervisor provides an open I/O network with support for Profibus DP, DPV1 and Modbus RTU master and slave. The advanced peer-to-peer communications on ALIN, together with the open I/O network delivers a distributable system.




## CONTROL NETWORK

Process Supervisor's control network provides peer-to-peer LIN communications with other control nodes such as Visual Supervisors and additional Process Supervisors. This communication is provided using Arcnet or Ethernet and is the method of connecting to Supervisory systems. Process Supervisor can also be used to communicate with any third party device that supports Profibus DP and Modbus RTU protocol.



- Peer-to-peer communication between nodes using LIN protocol
- Available on ARCnet or Ethernet cabling
- Profibus DP master
- Modbus RTU master and slave
- Simultaneous support for Profibus, Modbus and ARCnet or Ethernet

## OPEN I/O NETWORK




Process Supervisor is designed to use Eurotherm's 2500 for its distributed I/O system. It can also communicate with any third party device that supports Profibus DP or Modbus RTU protocol.

- Connectivity to 2500 distributed I/O via Profibus DPV1
- Available as Profibus DP master
- Supports Modbus RTU master and slave
- Simultaneous support for Profibus and Modbus

## CONFIGURATION

Eurotherm Project Studio 2000 contains the LINtools that is used to build both continuous and sequential control strategies. Eurotherm network explorer is also available to download files, and stop/start each individual Process Supervisor node.



## MODULAR HARDWARE

The modular hardware of the Process Supervisor comprise a chassis, a Connect Module and up to two Processor Modules.

### Connect Module

All external connections to the Processor Module are via the Connect Module, allowing the removal of a processor unit without any disturbance to the external cable interface. All the communication connectors and termination plug-ins are RJ45 format. The RJ45 connectors on the front panel can be wired for ALIN, Modbus RTU or Profibus DPV1 use, according to specification at the time of order. The pairs of RJ45 connectors on the left-hand side of the module are assigned to the left-hand processor and the right-hand connectors to the right-hand module. Each pair of connectors is wired in parallel to facilitate easy daisy chaining. Each processor has two 24V-supply connections. Additionally, a separate connector allows external battery, watchdog, and two software configurable alarm relays.



### Processor Module

Up to two Processor Modules can be installed on a chassis and can operate either independently (simplex), or in redundant mode. In redundant mode, one of the processors acts as a primary which is backed-up by the secondary in case of failure.

All external interfaces to the Processor Modules are via the Connect Module.



Processor modules can be supplied by two external 24V-power supplies to ensure operation in the event of power failure. The LEDs on the front panel of the Processor Modules provide comprehensive status indication, allowing for rapid verification and diagnostics.

The start-up mode of the module is selected from the front panel switch.

Inside the processor, a plug-in memory module holds both control strategies and operating software, enabling their rapid transfer to a spare instrument.

## REMOTE I/O

The Process Supervisor is designed to work with EurothermSuite Process Interface (2500) units. Up to 16 Process Interface units may be multi-dropped from the Process Supervisor and it can work with any third party I/O which supports Profibus DPV1 or Modbus RTU.



## EUROTHERM LIMITED

<http://www.eurotherm.co.uk>

### UK SALES OFFICE

**Eurotherm Ltd**  
Faraday Close Durrington Worthing  
Worthing BN13 3PL United Kingdom  
Tel. +44 (0)1903 205277 Fax +44 (0)1903 236465  
Email [info@eurotherm.co.uk](mailto:info@eurotherm.co.uk)

### US OFFICE

**Eurotherm**  
741-F Miller Drive  
Leesburg VA 20175-8993  
Tel. 1-703-443-0000 Fax 1-703-669-1300  
Web [www.eurotherm.com](http://www.eurotherm.com) Email [sales@eurotherm.com](mailto:sales@eurotherm.com)

© Copyright Eurotherm Limited 1999, 2000, 2002

All rights are strictly reserved. No part of this document may be reproduced, modified, or transmitted in any form by any means, nor may it be stored in a retrieval system other than for the purpose to act as an aid in operating the equipment to which the document relates, without the prior written permission of Eurotherm limited.

Eurotherm Limited pursues a policy of continuous development and product improvement. The specifications in this document may therefore be changed without notice. The information in this document is given in good faith, but is intended for guidance only. Eurotherm Limited will accept no responsibility for any losses arising from errors in this document.

